



9252 HYSSOP DRIVE RANCHO CUCAMONGA CA 91730

909.291.7550

www.cbmmotorsports.com

## MEFI relay pack

Connector:	Description:	Wire color:
<b>-These wires go to the fuse block-</b>		
Fan power (1 and 2)	Connect these wires to a full time 12v+ source. These wires supply power for the fans.	red w/black stripe (x2)
Ignition power	Connect this wire to a full time 12v+ source. This wire supplies power to the ignition/power relay.	red
Fuel pump power	Connect this wire to a full time 12v+ source. This wire supplies power to the fuel pump.	red w/black stripe
<b>-These wires come from the relay pack-</b>		
Ignition in	Connect this wire to a switched 12v+ source. This wire turns the computer on and off.	pink w/black stripe
ECM power in	Connect this wire to a full time 12v+ source. This wire powers the computer.	orange w/fuse block
Tach out	Connect this wire to tach signal input. This wire shows one pulse per revolution.	grey
Fan out (1 and 2)	Connect these wires to the fans. These wires power the fans when the computer triggers them.	red (x2)
Fuel pump out	Connect this wire to fuel pump. This wire powers the fuel pump when the computer triggers it.	red w/black stripe
*Coolant temp	Connect this wire to coolant gauge.	yellow
*Oil pressure	Connect this wire to oil pressure gauge.	tan

\*Opposite end must be connected to sender. See harness diagram for details.

\*FOR OFF-ROAD RACING ONLY, NOT FOR SALE IN CALIFORNIA FOR CA REGISTERED VEHICLES, NOT FOR USE IN CALIFORNIA.  
\*\* FOR SALE IN CALIFORNIA, FOR CA REGISTERED VEHICLES - APPROVED AND CERTIFIED BY CA RESOURCES BOARD.

© CBM Motorsports LLC 2013